

privest.®

FU9011

## Privest Wireless Alarm Control Panel, EN

The Privest wireless alarm system combines an elegant timeless design with user-friendly operability. With its 33 zones (32 wireless and 1 wired) and its four programmable outputs, the alarm control panel is the heart of the good feeling of security.

The innovative AM radio technology operates on a special frequency within the 868 MHz band that is reserved for wireless alarm systems. Programming and operation are easy thanks to the speech-supported menu navigation (English).

If an event occurs, residents are warned of dangers such as fire, water and burglaries or they are alarmed in case of an emergency via the integrated Piezo signalling device. In addition, an emergency call center or a mobile telephone can be contacted via an integrated speech dialling unit (AWAG). This makes the Privest wireless alarm system the perfect entry-level model among professional alarm systems.



### Product highlights:

- 868MHz wireless alarm center AM
- 32 wireless detectors and one wired zone
- Wide coverage
- Small dimensions
- Easy self-installation

## Privest Wireless Alarm Control Panel, EN

### Technical Data

Radio frequency	868.65 MHz AM
Voltage	230VAC
Emergency power supply	6x1.2V NiCd batteries or 6x1.5V AA alkali
Alarm zones	32 wireless zones / 1 wired zone
Alarm outputs	4 switching outputs + a signal generator output
Number of users	34
Speaker	Integrated for alarm and AWAG function
Microphone	Integrated
Telephone connection	Analog (PSTN)
Event storage	256
Dimensions (HxWxD)	196x240x45 mm
Weight	940g (incl. batteries)
Material	ABS
Display	Monochrome, 2-line
Language	English